



### 3 CHANNEL LEARNING RECEIVER

Code: MERX3-B3 (Regen) - 20m to 40m range

Code: MERX3-B1/S (Super Het.) - 60m to 80m range



#### Installation Instructions: New Installation

Select **Latch/Pulse** on links, before connecting power.  
Connect wires as required, LED will flash for 2 seconds on power up.

Code your transmitter as required.

Press & release the **Program** button once, LED will flash once. (Indicating channel 1.)

Hold the transmitter 1 metre away from the receiver & press the required button on the transmitter. The receiver LED will then flash to indicate that the transmitter has been accepted & is stored.

Press & release the **Program** button once, LED will flash twice. (Indicating channel 2.)

Hold the transmitter 1 metre away from the receiver & press the required button on the transmitter. The receiver LED will then flash to indicate that the transmitter has been accepted & is stored.

Press & release the **Program** button once, LED will flash thrice. (Indicating channel 3.)

Hold the transmitter 1 metre away from the receiver & press the required button on the transmitter. The receiver LED will then flash to indicate that the transmitter has been accepted & is stored.

Press & release the **Program** button once, LED will flash once for 2 seconds. (Indicating learn exit.)

**Please ensure that all transmitters being used on the receiver have the same code.**

#### Specifications:

<b>Power Requirements:</b>	12/24V AC/DC
<b>Frequency:</b>	403.55 / 433.92MHz
<b>Sensitivity:</b>	-105dBm
<b>Output Channels:</b>	3
<b>Learning Slots:</b>	1 per channel
<b>Output Contacts:</b>	Potential Free
	Change Over
	1 Amp Max

Manufactured By: MARTIN ELECTRONICS

PO BOX 82129 SOUTHDALE 2135 TEL: 011-433-4084 FAX: 011-680-3080

#### Type Approvals

