

CO-CJX2-D

Contactor AC



CJX2-D09,12



CJX2-D18



CJX2-D25



CJX2-D32



CJX2-D40,50,65,80,95

Application

CJX2 AC contactor D series (hereinafter referred to as contactor) is mainly used circuits of AC50Hz(or 60Hz), voltage up to 660V, and current up to 95A, for long-distance switching on/off the circuits and frequent start-up and control of AC motor, and it can be combined with appropriate thermal relay to constitute electromagnetic starter, in order to protect circuits that may subject to operating overload.

Main Technical Data

Type	CJX2 -D09	CJX2 -D12	CJX2 -D18	CJX2 -D25	CJX2 -D32	CJX2 -D40	CJX2 -D50	CJX2 -D63	CJX2 -D80	CJX2 -D95
Rated Insulation	660	660	660	660	660	660	660	660	660	660
Conventional Thermal Current	20	25	32	40	50	60	75	80	110	125
Rated Operational Current 380V/AC3	9	12	18	25	32	40	50	63	80	95
Power of Controlled (kW)	2.2	3	4	5.5		11	15	18.5	22	25
	4	5.5	7.5	11		18.5	22	30	37	45
	4	5.5	9	11		22	25	37	45	45
	4	5.5	9	11		22	30	37	45	45
	5.5	7.5	10	15		30	33	37	45	45
Installation	1. Two screw mounted 2. Din mounted (35mm)					1. Three screw mounted 2. Din mounted (35mm / 75mm)				