



UT261 series is used for determining 3-phase power phase sequence, missing phase indication, and motor phase rotation (UT261B). UT261A and UT261B can measure AC voltage of 40~700V and 90~600V respectively. These devices can operate in frequency range of 15~400Hz. UT261 are durable devices which can withstand impact from 2 meter's height. Test leads with protective tubing are included in optional accessories.

### SPECIFICATIONS

	Range	UT261A	UT261B
AC voltage (V)	90V~600V		√
	40V~690V	√	
Frequency (Hz)	15Hz~400Hz	√	√
Working current (A)		<1mA	<3mA
<b>Features</b>			
Phase sequence indication		LCD	LED
Missing phase indication		LCD	LED
Motor rotation indication			LED

### GENERAL CHARACTERISTICS

Power	<b>UT261A:</b> No battery required; <b>UT261B:</b> 9V battery (6F22)
Product color	Red and grey
Product net weight	<b>UT261A:</b> 160g; <b>UT261B:</b> 180g
Product size	123mm x 71mm x 29mm
Standard accessories	Battery ( <b>UT261B</b> ), test lead with alligator clip x 3
Standard individual packing	Gift box, English manual, carrying bag
Standard quantity per carton	20PCSpcs
Standard carton measurement	450mm x 325mm x 340mm
Standard carton gross weight	<b>T261A:</b> 9.8kg; <b>UT261B:</b> 10.3kg



● UT261A



● UT261B