

# LOW FREQUENCY POWER AMPLIFIER MEDIUM SPEED SWITCHING INDUSTRIAL USE

• Complement to KSD580

## ABSOLUTE MAXIMUM RATINGS ( $T_a = 25^\circ\text{C}$ )

Characteristic	Symbol	Rating	Unit
Collector-Base Voltage	$V_{CB}$	-100	V
Collector-Emitter Voltage	$V_{CE}$	-100	V
Emitter-Base Voltage	$V_{EB}$	-7	V
Collector Current (DC)	$I_C$	-5	A
Collector Current (Pulse)	$I_{CP}$	-8	A
Base Current (DC)	$I_B$	-0.5	A
Collector Dissipation ( $T_c = 25^\circ\text{C}$ )	$P_C$	1.5	W
Collector Dissipation ( $T_c = 25^\circ\text{C}$ )	$P_C$	30	W
Junction Temperature	$T_j$	150	$^\circ\text{C}$
Storage Temperature	$T_{stg}$	-55~150	$^\circ\text{C}$

•  $P_W \leq 10\text{ms}$ , Duty Cycle  $\leq 50\%$

## ELECTRICAL CHARACTERISTICS ( $T_a = 25^\circ\text{C}$ )


Characteristic	Symbol	Test Condition	Min	Typ	Max	Unit
Collector Emitter Sustaining Voltage	$V_{CE(sus)}$	$I_C = -3\text{A}$ , $I_B = -3\text{mA}$ , $L = 1\text{mH}$	-100			V
Collector Emitter Sustaining Voltage	$V_{CE(sus)1}$	$I_C = -3\text{A}$ , $I_B = -I_{B2} = -3\text{mA}$ $V_{BE}(\text{off}) = 5\text{V}$ , $L = 180\mu\text{H}$ Clamped	-100			V
Collector Emitter Sustaining Voltage	$V_{CE(sus)2}$	$I_C = -6\text{A}$ , $I_B = -1.2\text{mA}$ $I_{B2} = 3\text{mA}$ , $V_{BE}(\text{off}) = 5\text{V}$ $L = 180\mu\text{H}$ , Clamped	-100			V
Collector Cutoff Current	$I_{CE}$	$V_{CE} = -100\text{V}$ , $I_B = 0$			-10	$\mu\text{A}$
Collector Cutoff Current	$I_{CE1}$	$V_{CE} = -100\text{V}$ , $R_{BE} = 51\Omega$ $T_a = 125^\circ\text{C}$			-1	$\text{mA}$
Collector Cutoff Current	$I_{CE1}$	$V_{CE} = -100\text{V}$ , $V_{BE}(\text{off}) = 1.5\text{V}$			-10	$\mu\text{A}$
Collector Cutoff Current	$I_{CE2}$	$V_{CE} = -100\text{V}$ , $V_{BE}(\text{off}) = 1.5\text{V}$ $T_a = 125^\circ\text{C}$			-1	$\text{mA}$
Emitter Cutoff Current	$I_{EB}$	$V_{BE} = -5\text{V}$ , $I_C = 0$			-3	$\text{mA}$
DC Current Gain	$h_{FE}$	$V_{CE} = -2\text{V}$ , $I_C = -3\text{A}$	2000		15000	
	$h_{FE2}$	$V_{CE} = -2\text{V}$ , $I_C = -5\text{A}$	500			
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$	$I_C = -3\text{A}$ , $I_B = -3\text{mA}$			-1.5	V
Base-Emitter Saturation Voltage	$V_{BE(sat)}$	$I_C = -3\text{A}$ , $I_B = -3\text{mA}$			-2	V
Turn On Time	$t_{on}$	$I_C = -3\text{A}$ , $R_L = 17\Omega$		0.5		$\mu\text{s}$
Storage Time	$t_s$	$I_{B1} = -I_{B2} = -3\text{mA}$		1		$\mu\text{s}$
Fall Time	$t_f$	$V_{CE} = -50\text{V}$		1		$\mu\text{s}$

\* Pulse Test:  $P_W \leq 350\mu\text{s}$ , Duty Cycles  $\leq 2\%$

## $h_{FE}(1)$ CLASSIFICATION

Classification	R	O	Y
$h_{FE}(1)$	2000-5000	3000-7000	5000-15000

TO-220



1. Base 2. Collector 3. Emitter