Mini LED DC2.5-30V Red Volt Voltage Meter Display Digital

P/N: 190906

Product Features:

•

- The voltmeter use 0.36 inch digital tube display, with super small volume, area with only a coin similar
- o Connection is simple, just need to pick up two lines, a joint reverse protection, then do not burn
- Starting voltage is low, only 2.50 V, can correct measurement
- To achieve the best measurement precision, the voltmeter will measure the voltage according to the different automatic moving the position of the decimal point
- Can be used for measuring 18650 cell phone lithium battery nimh battery and other battery voltage, and motorcycle automobile battery voltage
- Can be used in all kinds of voltage measurement purposes

Technical Parameters:

o Power supply: don\\'t need the power supply, direct use of the test voltage as a power supply

Measurement range: DC2.50 - 30V

The minimum input: 2.50VThe maximum input: 30V

 \circ Operation temperature:-10 \sim 65 centigrade

Display mode: three 0.36 LED digital tube

o Display color: Red

update rate:about 500 ms/time

Permissible error: 1% (+ / - a word)

Physical size: 23 x 15 x 10 mm (L X W X H,not including installation ear)

Leadwire length: 15 cm