

单相通用滤波器 SINGLE PHASE FILTERS

- 常规通用单相滤波器，价格优惠，安装简单；
General single phase filter, low price, easy to instal.l
- 高频抑制性能优异，补充基板滤波电路高频性能不足；
Excellent interference-supression for high frequency.
- 低泄露电流，高品质元件，性能有保证。
Low leakage current and high quality components ensure the safety and reliability of filter.
- 适用于开关电源、UPS、自动售货机、绣花机、示波器、工业计算机、控制器等多种设备。
Suitable for the switching power supply, USP, automat, embroidery machine, oscillograph, industrial computer controller etc.



Specification

规格表

滤波器型号 PART No	端接方式 Connection IN OUT	额定电流 Rated current	额定电压 Rated voltage	工作频率 Line frequency	耐压等级 Hipot test voltage	工作温度 Temperature Range	最大漏电流 MAX leakage current
AN-6A4BL	■ ■	6A	120/250VAC	50/60Hz	线-线(L-L) 1500VDC/1Min 线-地(L-G) 2000VAC/1Min	25/085/21	1.0mA
AN-10A4BL	■ ■	10A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-20A4BL	■ ■	20A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-6A4HL	■ ■	6A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-10A4HL	■ ■	10A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-20A4HL	■ ■	20A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-6A4B23L	■ ■	6A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-10A4B23L	■ ■	10A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-20A4B23L	■ ■	20A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-6A4B23B	■ ■	6A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-10A4B23B	■ ■	10A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-20A4B23B	■ ■	20A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-6A4HB	■ ■	6A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-10A4HB	■ ■	10A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-20A4HB	■ ■	20A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-30FA4HB	■ ■	30A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-40A4CB	■ ■	40A	120/250VAC	50/60Hz		25/085/21	1.0mA
AN-50A4EB	■ ■	50A	120/250VAC	50/60Hz		25/085/21	2.0mA
AN-60A4EB	■ ■	60A	120/250VAC	50/60Hz		25/085/21	2.0mA
AN-80A4GB	■ ■	80A	120/250VAC	50/60Hz		25/085/21	2.0mA
AN-100A4GB	■ ■	100A	120/250VAC	50/60Hz		25/085/21	2.0mA
AN-150A4FB	■ ■	150A	120/250VAC	50/60Hz		25/085/21	2.0mA
AN-200A4FB	■ ■	200A	120/250VAC	50/60Hz		25/085/21	2.0mA

Schematic

电气原理图

