International Components Distributor

TEL JHB: (011) 493-9307

CAPE: (021) 535-3150 KZN: (031) 309-7692

FAX: (011) 493-9319

sales@mantech.co.za

## **FZ** SERIES PANEL MOUNT DIGITAL INSTRUMENTS



## **FEATURES**

- Front Panel access / mount
- Compact
- Long distance visibility
- Amp Meter Current isolated from supply

Model	Range	Resolution	Accuracy	Supply
FZ VM 12 D	0 to 90Vdc	0.1V	+/- 0.2V	8.5V to 16Vdc
FZ AM 10 D	0 to 10A continuous, 20A Peak	0.1A	+/- 0.2A	8.5V to 16Vdc

## Part number / Coding system

**FZ VM 12 A** (1) (2) (3) (4)

- (1) FZ = FAZE ELECTRONICS
- (2) Function. VM for voltmeter  $$\operatorname{AM}$$  for ampmeter
- (3) Range. 12=12V, 10=Amp, etc.
- (4) Type. A for AC / D for DC

Wiring Diagram / Connections				
VOLTMETER  Red = 12V power for electronics  Black = 0V power for electronics  Blue = Vin measuring input voltage  Black is common for measuring and supply  AMPMETER				
Red = 12V power for electronics Black = 0V power for electronics Yellow = Current Positive Green = Current Negative				
Dimensions & Panel Cutout				
Bezel dimensions: 36mm high, 72mm wide and 7.5mm thick.  Panel Cutout required: 26mm high x 50mm wide,  Mounting holes: 60mm centre to center, Centered horizontally and vertically				
Notes				
Durable and reliable for general purpose metering.				