



12V 6000rpm								
Reduction Gear Ratio	1/35	1/28	1/22	1/15	1/13	1/11	1/9.5	1/7
Lenth of Gear Box (mm)	22.0	22.0	22.0	26.5	26.5	26.5	26.5	26.5
No Load Speed (rpm)	168.8	210	270	393.8	450	506	630	810
No Load current (mA)	180	180	180	180	180	180	180	180
Torque (kg.cm)	8.0	6.6	5.3	4.7	4.1	3.1	2.4	1.9
Max Load Current (A)	1.6	1.6	1.6	1.6	1.6	1.6	1.6	1.6

**Notes:**

1. Screw can't into the motor internal more than 3.5mm.
2. Tolerances not otherwise specified decimal: ±0.3mm.

			<b>GB37Y360</b>		
			<b>181468</b>		